

### Introduction

Ferrite beads (or chips) are recommended for IDT clock products for power supply filtering of the main supply rails.

The five leading parameters and characteristics to consider when selecting ferrite bead are DC resistance, AC impedance, bias current rating, material, and package size. What is desired for good isolation is a low pass power filter. For that a bead with some DC resistance is best. High current power beads should be avoided. How much resistance depends on how much voltage drop is allowed and therefore the maximum current of the device being powered.

Some **DC resistance** is desirable to reduce the Q of the low pass LC filter. DC resistance in datasheets is usually 1.5 to 2 times the typical DC resistance. DC resistance should be measured with a 4-wire or Kelvin ohm meter. This is material dependent.

**AC impedance** characteristics are also material dependent. Examine the impedance curves. Impedance is normally measured and specified at 100 MHz. Select a bead with higher loss at 50 MHz.

**Bias current rating.** Ferrite beads are magnetic devices whose loss is affected by the bias current. When operating at close to maximum rating the impedance may decrease by half in some ferrite beads. Usually beads are now de-rated by manufactures.

**Material.** Beads in different form factors have similar DC resistance and impedance characteristics that use the same material.

### Examples of Suitable Ferrite Beads

Manufacture	Part Number	Z@100MHz	Package Size	DC Res.	Current (Ma)
Fair-rite	2504021217Y	120	0402	0.5	200
muRata	BLM15AG221SN1	220	0402	0.35	300
muRata	BLM15BB121SN1	120	0402	0.35	300
TDK	MMZ1005S241A	240	0402	0.18	200
TECSTAR	TB4532153121	120	0402	0.3	300
muRata	BLM18BB221SN1	220	0603	0.45	450
muRata	BLM18AG601SN1	600	0603	0.50	200
muRata	BLM18BD601SN1_PB	600	0603	0.65	200
Ceratech	HB-1T1608-601	600	0603	0.50	200
TDK	MMZ1608R301A	300	0603	0.20	500
muRata	BLM21A601R	600	0805	0.30	600
TDK	MMZ2012S601A	600	0805	0.30	600
STEWART	HZ0805E601R	600	0805	0.30	600
AssocCmpTch	CBG0805-600-50	600	0805	0.30	600

**Package size.** Manufactures may specify the package size in either mils (1 inch/1000) or millimeters (mm)

### Package Size Conversion Chart

mils	mm
0402 =	1005
0603 =	1608
0805 =	2012
1206 =	3216



**Corporate Headquarters**  
6024 Silver Creek Valley Road  
San Jose, CA 95138 USA

**Sales**  
1-800-345-7015 or  
408-284-8200  
Fax: 408-284-2775  
www.IDT.com

**Tech Support**  
email: [clocks@idt.com](mailto:clocks@idt.com)  
480-763-2056

DISCLAIMER Integrated Device Technology, Inc. (IDT) and its subsidiaries reserve the right to modify the products and/or specifications described herein at any time and at IDT's sole discretion. All information in this document, including descriptions of product features and performance, is subject to change without notice. Performance specifications and the operating parameters of the described products are determined in the independent state and are not guaranteed to perform the same way when installed in customer products. The information contained herein is provided without representation or warranty of any kind, whether express or implied, including, but not limited to, the suitability of IDT's products for any particular purpose, an implied warranty of merchantability, or non-infringement of the intellectual property rights of others. This document is presented only as a guide and does not convey any license under intellectual property rights of IDT or any third parties.

IDT's products are not intended for use in applications involving extreme environmental conditions or in life support systems or similar devices where the failure or malfunction of an IDT product can be reasonably expected to significantly affect the health or safety of users. Anyone using an IDT product in such a manner does so at their own risk, absent an express, written agreement by IDT.

Integrated Device Technology, IDT and the IDT logo are registered trademarks of IDT. Product specification subject to change without notice. Other trademarks and service marks used herein, including protected names, logos and designs, are the property of IDT or their respective third party owners.

Copyright 2013. All rights reserved.